




GLORYSTAR

7"

Media Player



USB Update



Plug and Play



LCD

Overview

The Glory Star 7" Media Player with a 1024x600 resolution and TN panel offers decent image quality and viewing angles. It's compact and portable, suitable for different applications. Equipped with an M-Star Chipset, it ensures smooth performance and efficient multimedia processing. Plug & Play functionality allows easy connection of SD cards or USB devices for convenient data transfer or content playback. The auto-start feature enables immediate operation upon power supply. With three activation modes (Loop, Sequential Loop, and Motion Sense), versatile usage is possible. VESA 30x75 compatibility allows for easy mounting, while the remote control and Kensington lock offer convenience and security. This product provides a versatile solution in a lightweight package.

Specification

Model	GAD073
Size	7"
Resolution	1024 x 600
Brightness	250cd/m2
Contrast	400: 1
Aspect Ratio	16 : 9
Active Display Area	154.2 x 85.9mm
Viewing Angle	U/D: 70°, 70° L/R: 50°,70°
Display Tech	LCD
Chipset	M-Star
Software Features	<ul style="list-style-type: none"> • Play back Features : Auto play, Repeat • Motion Sensor : Off,2Spot,30s,90s,45S Mute • COPY function: SD card, USB to update contents
Video Format	MPG、 MPEG、 MP4、 MKV、 RM、 RMVB、 FLV、 TS、 TRP、 M2TS
Audio Format	MP3、 WMA
Image Format	JPEG、 BMP、 PNG
Supported Media Card	USB 2.0 、 SD card
Speaker	1W x 2
Sensors	Motion Sensor
IR	Remote control receiver
LED	LED indicator
How to Update	SD card, USB to update contents Software upgrade: Put the upgraded "BIN" file into the USB flash drive, insert it into the machine, and select the "Software updatde (USB)" option to upgrade.
COPY function	<p>Select USB UPDATE (default 30S) in the menu, and the following two COPY states are as follows:</p> <ul style="list-style-type: none"> • 30S You only need to place the source file that needs to be COPY in the USB flash drive, and insert it into the USB flash drive within 30S after booting up to enter the COPY state. After COPY is completed, remove the USB flash drive • Protect files Place the "UPGRADE.FLG "file on the USB flash drive,When inserting a USB flash drive and an SD card into the machine interface at the same time. Power on and automatically enter the COPY state,COPY is done,Just unplug the USB flash drive. Note: The file name cannot be less than a single digit or a single letter.
Color	Black
Chassis	Plastic
Functional outlets	USB、 DC、 Toggle switch 、 SD
Button	+ , Menu, -
Included in Box	Media player, Adapter, remote control, user manual
Consumption	5W
Power Input	DC 12V 1.2A
Operating Environment	Working Temperature at 0-45 degree celsius
OSD Language	Multi languages
Mounting	Shelf Mount; VESA 30 x 75
Certification	CE, FCC, RoHS
Dimensions (LxWXH)	189.5 x 119.35 x 35mm
Weight	0.35kg
Box size / each pc (LxWXH)	262×130×68mm
Box Weight	0.63kg
Master Box size (LXWXH)	55.5×28×37.5cm
Master Box Weight	13.2kg
Pieces/ Carton	20pcs

Mounting Options

Shelf Mount	FIX014
	FIX017
	WM015012S

CONTACT US

United States	Hong Kong	ShenZhen
1440 N. Harbor Blvd Suite 900 Fullerton, CA 92835, USA 626 228 5927	Flat D, 5/F, Excelsior Building, 364 Nathan Road, Kowloon, Hong Kong 852 23762803	Bldg. 9, 4/F Zhong Yuntai Technology Industrial Park, Tangtou No.1 Road, Shiyan Street, Baoan, ShenZhen, PRC 86 755 2600 1808

To find out more about our extensive range of Glory Star solutions, go to www.glorystargroup.com, or call the office nearest you. For more information, please contact us at sales@glorystargroup.com. Glory Star reserves the right to change or update, without notice, any information contained herein; to change, without notice, the design, construction, materials, processing or specifications of any products; and to discontinue or limit production or distribution of any products. Glory Star, the Glory Star logo, STAR CONTROL and STAROS are either trademarks or registered trademarks of Glory Star Group Limited. All other trademarks are the property of their respective owners.